



PT/PR-200iR-x-X Series

Fiber Optic RS-232 or RS-422 Data Transmission System

Installation Instructions

Table of Contents

- 1.0 Product Description3
- 2.0 Installation3
- 3.0 Modem Optical Connection.....4
- 3.1 Product Signal Format & Specifications4
- 4.0 Troubleshooting.....5

1.0 Product Description

Meridian's product PT/PR-200iR-x-X series products are fiber optic modems that transmit one channel of one channel of uni-directional RS-422, or RS-232 data over one optical fibers using FM transmission technologies. This product series uses Meridian's standard 1-slot wide chassis mount card assembly and plugs into the following Meridian chassis: SR-500/S, SR-1000, SR-1000/S, SR-1200/S, SR-1500/S, and SR-2001 & SR-2000 series 19" equipment chassis.

2.0 Installation

Series PT-200iR-x-X and PR-200iR-x-X products are one-slot wide cards and, as such, occupy only one slot in Meridian's standard chassis (SR-500/S, SR-1000, SR-1000/S, SR-1200/S, SR-1500/S, and SR-2001 & SR-2000 series 19" equipment chassis). To install in the chassis, orient the card with the Meridian logo at the top of the module and slide onto the top and bottom card guides in the chassis. Press securely on the top and bottom of the module to ensure that it is fully seated in the chassis so that the electrical connector mates with the chassis-mounted motherboard. Once installed, manually tighten the two thumbscrews located at the top and bottom of the card. Do not use tools to secure these and do not over tighten.

Note: A fully loaded subrack should have forced-air cooling to avoid excessive heat generation inside the chassis. A fan assembly tray (P/N FA-2000) with three (3) fans is available and should be installed under the 19" SR-2000/1 whenever possible.

Front Panel Indicators – There is a front panel power indicator on the PT/PR-200iR-x-X series modems.

Product Part Numbers

These modems are available in either one or two fibers and with 3-pin terminal connectors. The table below identifies these various products and their associated part numbers.

PT/PR-200iR Part Numbers					
Transmitter (Side A)	Receiver (Side B)	# Fibers & Type	Transmit Wavelength	Receive Wavelength	Data Connector
PT-200iR-3-0	PR-200iR-3-0	1 – MM	850/1300 nm	1300/850 nm	3-pin block
PT-200iR-3-1	PR-200iR-3-1	1 – SM	1310/1 550 nm	1550/1310 nm	3-pin block
PT-200iR-4-0	PR-200iR-4-0	1 – MM	850/1300 nm	1300/850 nm	3-pin block
PT-200iR-4-1	PR-200iR-4-1	1 – SM	1310/1 550 nm	1550/1310 nm	3-pin block

3.0 Modem Optical Connection

The PT/PR-200iR 1-fiber data modems are single fiber modems and, as such, must be connected in 'pairs'. In other words, a PT unit must be optically connected to the corresponding PR unit at the other side. A PT unit will not communicate with another PT unit. Likewise, a PR unit will not communicate with another PR module.

3.1 Product Signal Format & Specifications

The PT & PR-200iR series products transmit and receive the following signals:

Signal Type	Channels	Transmit	Receive
RS-232 (Tx & Rx data)	1	PT-200iR-3	PR-200iR-3
RS-422 (Tx & Rx data)	1	PT-200iR-4	PR-200iR-4

The tables below identify the specifications for the various signals that these modems transmit/receive.

Data	
Formats	RS-232
Date Rate (RS-232)	DC to 125Kb/s
Data Rate (RS-422)	DC to 300Kb/s
Bit Error Rate (BER)	Better than 10^{-9}

Connectors	
Data	One, 3-pin terminal blocks (see front-panel diagrams for input/output connections)
Optical	Singlemode – ST or FC Multimode - ST

The data input/output connectors are identified on the attached front-panel diagrams.

Optical Specifications						
Fiber Type/Size (um)	Optical Output (dBm)	Rx Sensitivity (dBm)	Optical Budget (dB)	Wavelength (nm)	Optical connector	Optical Dynamic Range (dB)
Multimode (FP Laser) 62.5/125	-3	-24	21	1300/850	ST	24
Singlemode (FP Laser) 9/125	-3	-24	21	1310/1 550	ST, FC	24
Singlemode (DFB Laser) 9/125	+3	-24	27	1310/1 550	ST, FC	24

4.0 Troubleshooting

Below is a listing of several problems that may arise during the installation & operation of the modules. If you are having difficulty installing or operating the modules please refer to this list below.

- Problem:** *Module does not fit in chassis slots*
Action: Check module orientation. Meridian "Globe" must be oriented on the top left hand side of the module
Make sure the card guides in the chassis are aligned with the extrusion on the module
- Problem:** *Card power LED does not light when power to the module/subrack is applied or power indicator turns on and off*
Action: Check power supply to ensure that it is plugged in and turned on. If flashing continues, move module to another chassis or location in the same chassis, if available.
- Problem:** *No data*
Action: 1) Check to ensure fibers properly connected on the 2-fiber units
2) Check to ensure that the electrical pins are properly connected

If the problem still persists after reviewing the above items, please contact Meridian technical support (516-285-1000).